

5 YEARS WARRANTY

IP20

CE

UK CA

RoHS Compliant

RoHS Compliant

# SIGNBRIDGE PLUS INDOOR 100 W LED DRIVER

## INSTALLATION GUIDE FOR MODEL: **BPSP.I-100-12/24V.3**

### READ THE INSTRUCTIONS CAREFULLY BEFORE MOUNTING

- Power supply operating temperature is from -20 to +50 °C. To ensure adequate ventilation, mounting power supplies without a secondary enclosure is recommended.
- Space power supplies by standard knockout locations 19 mm minimum. If two or more power supplies are used, spacing must be at least 25 mm end-to-end, and 102 mm on each side. Power supply spacing to thermoplastic, wood, fibre, or other combustible enclosure materials must be 25 mm.
- Ensure power supplies are not overloaded by verifying :

FOR	OUTPUT CURRENT IS	FOR BEST PERFORMANCE RECOMMENDING
12V	< 8.33 A	< 6.66 A
24 V	< 4.17 A	< 3.34 A

- Use of photocells or timing device is recommended to ensure power supplies are off during day light hours, when sign illumination is not needed. Higher daytime temperatures and unnecessary operation may shorten power supply lifetime.

